

KODAK Solar Off Grid Inverter

OGX5.48a



Solar Off Grid Inverter

Features

- Pure sine wave solar inverter
- Detachable LCD control module with multiple communications
- Wide DC input range
- Built-in Wi-Fi for mobile monitoring (Android/iOS App is available)
- Supports USB On-the-Go function
- Reserved communication port for BMS (RS485, CAN-BUS or RS232)
- Smart battery charger design for optimized battery performance
- Battery independent function
- Built-in anti-dust kit
- Parallel operation up to 9 units

Models:

KODAK Solar Off Grid Inverter OGX 5.48a



Parallel
Capability



WiFi
Communication



Compatible
to generator



Detachable
LCD module



USB
On-the-Go



BMS
Communication



App
Download
Available



IP20



KODAK Solar Off Grid Inverter

OGX 5.48a

SPECIFICATIONS

MODEL	OGX 5.48a
Rated Power	5000VA/5000W
INPUT	
Voltage	230 VAC
Voltage Range	110-280 VAC
Frequency Range	50 Hz/60 Hz (Auto sensing)
OUTPUT	
AC Voltage Regulation (Batt. Mode)	230VAC \pm 5%
Overload capacity	5s@ \geq 150% load; 10s@110%-150% load; 100ms@ \geq 200% load
Efficiency (Peak)	50 Hz \pm 0.1 Hz or 60Hz \pm 0.1 Hz
Transfer Time	93 %
Waveform	15 ms (For Personal Computers); 20 ms (For Home Appliances)
Max. Charger Rate	5 minutes
BATTERY	
Battery Voltage	48 VDC
Floating Charge Voltage	54 VDC
Overcharge Protection	63 VDC
SOLAR CHARGER & AC CHARGER	
Solar Charger Type	MPPT
Maximum PV Array Power	5000 W
MPP Range @ Operating Voltage	120 - 430 VDC
Maximum PV Array Open Circuit Voltage	450 VDC
Maximum Solar Charge Current	100 A
Maximum AC Charge Current	100 A
Maximum Charge Current	100 A
PHYSICAL	
Dimension, D x W x H (mm)	140 x 295 x 468
Net Weight (kgs)	12.0
Communication Interface	USB/RS232/RS485/Wifi
ENVIRONMENT	
Humidity	5% to 95% Relative Humidity (Non-condensing)
Operating Temperature	-10°C to 50°C
Storage Temperature	-15°C to 60°C

All information contained in this document is subject to change without notice.



For further information visit www.bluemountainpv.com
© 2021 Blue Mountain Energy LTD. The Kodak trademark, logo and trade dress are used under license from Kodak.
Blue Mountain Energy Ltd. Crown House, 27 Old Gloucester Street, London WC1N 3AX
Made in China